



CÔNG TY TNHH THƯƠNG MẠI XUẤT NHẬP KHẨU SÔNG XANH

Địa chỉ: 15 đường 179, Phường Tăng Nhơn Phú,
TP. Hồ Chí Minh

ĐT: 0988 814 153

E-mail: songxanh468@gmail.com

Website: songxanhvietnam.com

TỦ TRUNG TÂM BÁO CHÁY HORING AH-00212

1. ĐẶC ĐIỂM NỔI BẬT

- Chức năng chống báo giả (Accumulation Function) giúp giảm thiểu báo giả do tín hiệu bất thường mà không ảnh hưởng khả năng phát hiện cháy.
- Mỗi Zone có hai đèn LED riêng hiển thị Báo cháy và Đứt mạch.
- Nút Test Zone dạng nhấn giúp tăng độ bền và hạn chế lỗi tiếp xúc.
- Logic Switch giúp tránh hư hỏng do điện áp không ổn định.
- Chế độ tiết kiệm nguồn cho đèn hiển thị ngoài khi mất điện, đèn vẫn nhấp nháy khi có báo cháy.
- Có thể chuyển đổi sang điều khiển hút khói, sprinkler hoặc foam.
- Nhấn Zone có thể thay đổi dễ dàng.
- Hỗ trợ bảng hiển thị phụ AH-02124.

2. THÔNG SỐ KỸ THUẬT

Thông số	AH-00212 (1–10 Zone)
Nguồn	220VAC/50Hz
Ắc quy	24VDC 1.2Ah
Điện áp sạc	26VDC, 100–400mA
Điện trở vòng dây	< 50Ω
Đầu báo nhiệt	Không giới hạn*
Đầu báo khói	30 đầu báo/Zone
Dòng ngõ ra tối đa	1A
Điện trở cuối tuyến	10kΩ
Vật liệu	Thép 1.2mm
Màu sắc	Trắng ngà
Kích thước	350×285×105 mm



AH-00212

Fire Alarm Control Panel

Characteristics

- This unit has Accumulation function, it can minimize the false alarm that caused by unstable pulse or any abnormal signal (false alarm) and no effect on the function of fire alarm at all.
- Each zone uses two different LED to indicate Fire alarm and Disconnection.
- Zone test switch uses single-loop press type to improve the twisting switch that its contact failure will caused by dust and improper use.
- Logical switch is different from traditional switch that needs to switch over higher voltage directly, it can prevent the damage caused by unstable voltage.
- External indicator power-save device can select Light ON or OFF under normal condition during power-off status, and stay blinking during alarm status which extend the operation life of control panel. (Prevent the control panel loss its function by wear-off on battery under power-off period)
- Easy to switch from fire alarm to smoke evacuation, sprinkling or foam system.
- Movable zone indication labels, they can be easily changed without affect its magnificent appearance.
- Annunciator is available on model AH-02124.

Specifications

Model	AH-00212 (1~10 zone)	AH-00212 (1 zone)
Power	220V AC/50Hz *Others also available	
Battery Capacity	24V DC 1.2Ah	24V DC 0.8Ah
Charging Voltage, Current	26V DC 100~400mA *With auto adjustment function	
Exterior Resistance	Round-trip under 50Ω	
# of heat detectors connected	No limit *Except electronic-type	
# of smoke detectors connected	30/zone *Horing Lih manufactured	
Max. Output Current	1A	500mA
End of Line Resistor	10kΩ *One per zone	
Material	1.2mm steel plate	
Color	Ivory white *Others also available	
Dimensions	350mm (H) x 285mm (W) x 105mm (D)	280mm (H) x 160mm (W) x 70mm (D)



AH-02124 Annunciator